

CROSS REFERENCE TO RELATED APPLICATIONS

5

10 Field of the Invention

15

35

to a reset state.

FIG. 11 is an operation timing diagram of the phase detector of FIG. 10. An operation of the phase detector of FIG. 10 will be described hereinafter with reference to FIG. 11. In an initial state (before time t_0), an output UPN of the NAND gate G22 has a high level, and an output RESETn of the NAND gate G23 also has the high level. When a reference clock REFCLK has the high level at the time t_0 , an output LC1 of the NAND gate G21 has the low level. Thereby, an output LO1 of a NAND gate G26 in the S-R flip-flop 21 reaches the high level, and an output LI1 of a NAND gate G27 reaches the low level.

Thereafter, when a clock signal CLK reaches the high level at time t_1 , an output LC2 of the NAND gate G24 reaches the low level, subsequently an output LO2 of a NAND gate G28 in the S-R flip-flop 22 reaches the high level, and an output LI2 of a NAND gate G29 reaches the low level.

Thereafter, when the reference clock REFCLK reaches the low level at time t_2 , the output LC1 of the NAND gate G21 reaches the high level, subsequently the output UPN of the NAND gate G22 reaches the low level, and an output UP of the inverter IV21 reaches the high level.

Subsequently, when the clock signal CLK reaches the low level at time t_3 , the output LC2 of the NAND gate G24 has the high level. Thereby, the output RESETn of the NAND gate G23 reaches the low level, subsequently the output UPN of the NAND gate G22 reaches the high level, and the output UP of the inverter IV21 reaches the low level.

Thereafter, when the reference clock signal REFCLK reaches the high level at time t_4 , an operation of time t_1 to t_4 is repeated.

In FIG. 10, a time difference between when the output UPN of the NAND gate G22 reaches the high level at a falling of the clock signal CLK and when the reference clock signal REFCLK rises to start initialization of the next clock cycle is assumed to be Δt_{31} . Then, the larger a phase delay time Δt_{11} of the clock signal CLK with respect to the reference clock signal REFCLK is, the smaller Δt_{31} becomes.

When frequencies of the reference clock signal REFCLK and clock signal CLK increase, Δt_{31} decreases and approaches zero. When Δt_{31} indicates a negative value, and when the reference clock signal REFCLK rises in the next clock cycle, the output UPN of the NAND gate G22 remains at the low level, the output LC1 of the NAND gate G21 cannot be set to the low level, and normal operation is not realized.

That is, a maximum operation frequency of the conventional phase detector shown in FIG. 10 is defined by the clock frequency at which Δt_{11} increases and Δt_{31} becomes zero. In a conventional example, when a phase delay of the clock signal CLK is large with respect to the reference clock signal REFCLK, a timing margin from a point of definition of the signal UPN as a previous signal of the signal UP until rising of the reference clock signal REFCLK at a start point of the next cycle is reduced. Therefore, the maximum operation frequency is lowered.

An example in which the phase delay of the clock signal CLK is large with respect to the reference clock signal REFCLK has been described above. However, the similar problem even occurs when the phase delay of the clock signal CLK is small with respect to the reference clock signal REFCLK. In this case, the circuit is initialized not with the reference clock signal REFCLK but with the rising of the clock signal CLK.

SUMMARY OF THE INVENTION

According to the present invention, there is provided a phase detector configured to output an up signal when a first clock signal is ahead of a second clock signal in phase, and outputting a down signal when said first clock signal is behind said second clock signal in phase, said phase detector comprising:

first, second and third flip-flops;

an F/F control circuit configured to set an output state of said first flip-flop based on outputs of said second and third flip-flops, setting the output state of said second flip-flop based on the outputs of said first and third flip-flops, and setting the output state of said third flip-flop based on the outputs of said first and second flip-flops; and

an up/down signal output circuit configured to output said up signal and the down signal based on the outputs of said second and third flip-flops.

5 BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a circuit diagram of a first embodiment of a phase detector 10 according to the present invention.

FIG. 2 is an equivalent circuit diagram of FIG. 1.

FIG. 3 is a circuit diagram of an S-R flip-flop of FIG.
10 2.

FIG. 4 is an operation timing diagram of the phase detector 10 of FIG. 1.

FIG. 5 is a diagram showing a relation between a power source voltage (V) and a maximum operation frequency (MHz).

FIG. 6 is a block diagram of a PLL circuit constituted using the phase detector 10 of FIG. 1.

FIG. 7 is an operation timing diagram of the PLL circuit of FIG. 6.

FIG. 8 is a circuit diagram of a second embodiment of the phase detector 10 according to the present invention.

FIG. 9 is a circuit diagram showing an internal constitution of the S-R flip-flop of FIG. 8.

FIG. 10 is a circuit diagram showing the internal constitution of a conventional phase detector.

FIG. 11 is an operation timing diagram of the phase detector of FIG. 10.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

A phase detector and phase locked loop circuit (PLL circuit) of the present invention will concretely be described hereinafter with reference to the drawings.

(First Embodiment)

FIG. 1 is a circuit diagram of a first embodiment of a phase detector 10 according to the present invention. The phase
35 detector 10 of FIG. 1 includes three S-R flip-flops 1 to 3 each of which is constituted of two NAND gates, NAND gates G1 to G6, and inverters IV1 to IV6.

The S-R flip-flop 1 has two NAND gates G7 and G8, one NAND gate G7 performs a NAND operation between a set input terminal RL and an output RI of the other NAND gate G8, and the other NAND gate G8 performs the NAND operation between a reset input terminal RS and an output RR of the NAND gate G7. The output of the NAND gate G7 forms the output of the S-R flip-flop 1.

When the S-R flip-flops 1 to 3 are shown by blocks, the NAND gate G5 and inverter IV5 are replaced with an AND gate G5a, and similarly the NAND gate G6 and inverter IV6 are replaced with an AND gate G6a in the circuit of FIG. 1, the circuit is replaced with a circuit diagram of FIG. 2. An internal constitution of the S-R flip-flops 1 to 3 of FIG. 2 is shown by a circuit of FIG. 3.

The NAND gate G1 of FIG. 2 performs the NAND operation between a reference clock signal REFCLK and a clock signal CLK. More concretely, when at least one of the reference clock signal REFCLK and clock signal CLK has a low level, the NAND gate G1 outputs a high-level signal, and the S-R flip-flop 1 is brought to a reset state.

When the S-R flip-flop 1 is in the reset state, and the reference clock signal REFCLK is at a high level, the NAND gate G2 brings the S-R flip-flop 2 to the set state.

When the S-R flip-flop 1 is in the reset state, and the clock signal CLK is at the high level, the NAND gate G3 brings the S-R flip-flop 3 to the set state.

When both the S-R flip-flops 2 and 3 are in the set state, the NAND gate G4 brings the S-R flip-flops 2 and 3 to the reset state and the S-R flip-flop 1 to the set state.

When the S-R flip-flop 2 is in the set state, and the S-R flip-flop 3 is in the reset state, the AND gate G5a of FIG. 2 outputs a high-level UP signal. When the S-R flip-flop 3 is in the set state, and the S-R flip-flop 2 is in the reset state, the AND gate G6a of FIG. 2 outputs a high-level DOWN signal.

FIG. 4 is an operation timing diagram of the phase detector 10 of FIG. 1. An operation of the phase detector 10 of FIG. 1 will be described hereinafter with reference to the operation timing diagram of FIG. 4.

RS low → output RI high → output RR low → output RESETn high) is not determined by a pulse of the UP signal. Therefore, the maximum operation frequency becomes high. This characteristic is particularly important when the phase detector 10 is operated at a low voltage. This is because the phase detector 10 is operated at the low voltage, gate delay is then generated, and the operation frequency tends to be lowered.

FIG. 5 is a diagram showing a relation between a power source voltage (V) and the maximum operation frequency (MHz), and shows a circuit simulation result of the maximum operation frequency of the phase detector 10 using a 0.35 μ m CMOS technique. In FIG. 5, a circle plot indicates a property of the present embodiment, and a cross plot indicates a conventional property.

As shown in FIG. 5, an operation rate of the present embodiment is higher than that of the conventional example by about 40% at the power source voltage in a range of 1.2 V to 2 V.

FIG. 6 is a block diagram of the PLL circuit constituted using the phase detector 10 of FIG. 1. The PLL circuit of FIG. 6 includes: a charge pump 11 for outputting a voltage signal in accordance with the UP signal and DOWN signal outputted from the phase detector 10; a loop filter 12 for removing a high frequency component from the voltage signal outputted from the charge pump 11; a voltage control oscillation circuit 13 which oscillates at a frequency in accordance with an output of the loop filter 12; and a clock buffer 14, connected to an output terminal of the voltage control oscillation circuit 13, for outputting the clock signal CLK.

Additionally, as omitted from FIG. 6, a signal constituted by frequency-dividing the clock signal CLK outputted from the clock buffer 14 may be supplied to the phase detector 10 and compared in phase with the reference clock signal.

FIG. 7 is an operation timing diagram of the PLL circuit of FIG. 6, FIG. 7A shows that the phase of the reference clock signal REFCLK is ahead of the phase of the clock signal CLK, and FIG. 7B shows that the phase of the reference clock signal REFCLK is behind the phase of the clock signal CLK.

In FIG. 7A, the phase detector 10 outputs the high-level UP signal, and the charge pump 11 controls so that the output voltage goes up. On the other hand, in FIG. 7B, the phase detector 10 outputs the high-level DOWN signal, and the charge pump 11 controls so that the output voltage goes down.

Since the phase detector 10 of the present embodiment sets the respective outputs of three flip-flops 1 to 3 for controlling generation of the UP and DOWN signals without being directly related to logic of the UP and DOWN signals. Therefore, the UP and DOWN signals can correctly be outputted in accordance with the phase difference between the reference clock signal REFCLK and the clock signal CLK regardless of a magnitude of the phase difference between both signals.

That is, according to the first embodiment, even when the phase difference between the reference clock signal REFCLK and the clock signal CLK is large, the UP and DOWN signals can correctly be outputted, and the maximum operation frequency can therefore be set to be higher than a conventional maximum operation frequency.

(Second Embodiment)

A second embodiment is different from the first embodiment in logic of a set input terminal and reset input terminal of the S-R flip-flop.

FIG. 8 is a circuit diagram of the second embodiment of the phase detector 10 according to the present invention. The phase detector 10 of FIG. 8 includes three S-R flip-flops 1a, 2a and 3a in which the set and reset input terminals have a positive logic, AND gates G2a, G3a, G4a, G5a and G6a, NAND gate G1, and inverters IV1 to IV3.

The S-R flip-flop 1a is brought to the reset state when the output of the NAND gate G1 has the high level, and is brought to the set state when the output of the AND gate G4a has the high level.

The S-R flip-flop 2a is brought to the set state when the output of the AND gate circuit G2a has the high level, and is brought to the reset state when the output of the AND gate circuit G4a has the high level.

The S-R flip-flop 3a is brought to the set state when the output of the AND gate circuit G3a has the high level, and is brought to the reset state when the output of the AND gate circuit G4a has the high level.

5 FIG. 9 is a circuit diagram showing an internal constitution of the S-R flip-flop of FIG. 8. As shown in FIG. 9, each of the S-R flip-flops 1a, 2a and 3a has NOR gates 6, 7 and inverter 8. The NOR gate 6 performs a NOR operation between the set input terminal and the output terminal of the NOR gate 7, the NOR gate 7 performs the NOR operation between the reset input terminal and the output terminal of the NOR gate 6, the inverter 8 reverses the output of the NOR gate 6, and the output of the inverter 8 forms the output of each flip-flop.

15 Also in the second embodiment, even when the phase difference between the reference clock signal REFCLK and the clock signal CLK is large, the UP and DOWN signals can correctly be outputted, and therefore the maximum operation frequency can be set to be high.

20 In the aforementioned first embodiment, an example in which the NAND gate and inverter are combined to constitute the phase detector 10 has been described. In the second embodiment, an example in which the NAND gate, AND gate and inverter are combined to constitute the phase detector 10 has been described. However, the type of the gate constituting the phase detector 10 is not particularly limited.

25